# FOREIGN TECHNOLOGY DIVISION

EVALUATION OF PARAMETERS OF THE OSCILLATORY MOTION
OF DIGITAL SERVO SYSTEM IN A STEADY-STATE MODE

by

V.P. Strakhov, Ye.G. Kuznetsova

DTIC
ELECTE
JAN 5   1982

A

82 01 04 109

EDITED TRANSLATION

EVALUATION OF PARAMETERS OF THE OSCILLATORY MOTION OF DIGITAL
SERVO SYSTEM IN A STEADY-STATE MODE

By: V.P. Strakhov, Ye.G. Kuznetsova

English pages: 5

U. S. BOARD ON GEOGRAPHIC NAMES TRANSLITERATION SYSTEM

Block	Italic	Transliteration	Block	Italic	Transliteration
А а	*А а*	A, a	Р р	*Р р*	R, r
Б б	*Б б*	B, b	С с	*С с*	S, s
В в	*В в*	V, v	Т т	*Т т*	T, t
Г г	*Г г*	G, g	У у	*У у*	U, u
Д д	*Д д*	D, d	Ф ф	*Ф ф*	F, f
Е е	*Е е*	Ye, ye; E, e*	Х х	*Х х*	Kh, kh
Ж ж	*Ж ж*	Zh, zh	Ц ц	*Ц ц*	Ts, ts
З з	*З з*	Z, z	Ч ч	*Ч ч*	Ch, ch
И и	*И и*	I, i	Ш ш	*Ш ш*	Sh, sh
Й й	*Й й*	Y, y	Щ щ	*Щ щ*	Shch, shch
К к	*К к*	K, k	Ъ ъ	*Ъ ъ*	"
Л л	*Л л*	L, l	Ы ы	*Ы ы*	Y, y
М м	*М м*	M, m	Ь ь	*Ь ь*	'
Н н	*Н н*	N, n	Э э	*Э э*	E, e
О о	*О о*	O, o	Ю ю	*Ю ю*	Yu, yu
П п	*П п*	P, p	Я я	*Я я*	Ya, ya

*ye initially, after vowels, and after ъ, ь; e elsewhere.
When written as ё in Russian, transliterate as yё or ё.

RUSSIAN AND ENGLISH TRIGONOMETRIC FUNCTIONS

Russian	English	Russian	English	Russian	English
sin	sin	sh	sinh	arc sh	sinh⁻¹
cos	cos	ch	cosh	arc ch	cosh⁻¹
tg	tan	th	tanh	arc th	tanh⁻¹
ctg	cot	cth	coth	arc cth	coth⁻¹
sec	sec	sch	sech	arc sch	sech⁻¹
cosec	csc	csch	csch	arc csch	csch⁻¹

Russian	English
rot	curl
lg	log

EVALUATION OF PARAMETERS OF THE OSCILLATORY MOTION OF DIGITAL SERVO SYSTEM IN A STEADY-STATE MODE

V.P. Strakhov, Ye.G. Kuznetsova
Moscow Aviation Institute

Examined is a digital servo system (TsSS) characterized
by the quantization of a signal with respect to level and
time. The steady-state mode in the system is characterized
by the emergence of an oscillating motion. The dependence of
parameters of the oscillating motion on parameters of the
system is given.

A TsSS with a three-positional relay characteristic of the con-
trol element was examined in reference [2]. Shownis the possibility
of an analysis of the dynamics of the TsSS by means of the represen-
tation of its motion on a phase surface in the presence of quantiza-
tion of the signal with respect to level and time.

The purpose of this work is to evaluate parameters of the os-
cillatory motion in the transient and steady-state modes.

The trajectory of the representing point, which characterizes
the behavior of the TsSS on the phase plane, will consist of segments
each of which can be described by the equation of trajectories:

$$X = X_0 + Y_0 - Y_1$$
$$+ \Phi(\delta) \ln \frac{Y_0 - \Phi(\epsilon)}{Y + \Phi(\epsilon)} \tag{1}$$

with the appropriate values of $\Phi_i(\delta)$.* [Translator's note: see
footnote on next page.]

1

Let us examine the case when the representing points M_1 and M_2 during time T_μ occupy the extreme positions H and C, respectively, (Fig. 1).


Fig. 1. Determination of parameters of the oscillatory motion in the transient and steady-state modes.

The maximum overswing in the transient mode with respect to the position of equilibrium corresponds to X'_{MAKC} for the trajectory of motion of the representing point M_1 and X''_{MAKC} for the trajectory of motion of the representing point M_2. $X''_{MAKC} = X_s + a_1 b_1$.

Having taken in quation (1)

$$\Phi(\delta) = 0; \quad X_0 = 0.5 \Delta_x; \quad Y_0 = 1,$$

we get

$$X_s = 0.5 \Delta_x + 1 + Y.$$

Having substituted into equation of line ND: $Y = \dfrac{1}{e^{T_\mu} - 1} X - \dfrac{0.5 \Delta_y}{e^{T_\mu} - 1}$ [2] the value X_s, after conversions, we obtain $Y_s = \dfrac{1}{e^{T_\mu}}$, then

$$X_s = \frac{e^{T_\mu} - 1}{e^{T_\mu}} + 0.5 \Delta_x.$$

---

*The change in the velocity and coordinate are described, correspondingly, by these equations:

$$Y = Y_0 e^{-\tau} + \Phi(\delta)(1 - e^{-\tau}), \quad (2) \qquad X = X_0 + Y_0(1 - e^{-\tau}) + \Phi(\delta)[\tau - (1 - e^{-\tau})]. \quad (3)$$

2

From equation (1), having assumed that $X_0 = 0; Y = 0; Y_0 = Y_c; X = a_1b_1$, we get

$$a_1b_1 = \frac{1}{e^{T_u}} - \ln\left(\frac{1}{e^{T_u}} + 1\right),$$

$$X'_{\text{макс}} = \frac{e^{T_u} - 1}{e^{T_u}} + 0{,}5\Delta_x + \frac{1}{e^{T_u}} \cdot \ln\frac{(1 + e^{T_u})}{e^{T_u}},$$

or

$$X'_{\text{макс}} = T_u + 1 + 0{,}5\Delta_x - \ln\left(1 + e^{T_u}\right),$$

$$X''_{\text{макс}} = X_c + a_2b_2. \tag{4}$$

The segment BC is numerically equal to the time of the comparison of codes T_u, then $X_c = T_u - 0{,}5\Delta_x$.

From equation (1), having assumed that $\Phi(\delta) = -1; X_0 = 0; Y_0 = Y_c = 1; X = a_2b_2; Y = 0$, we obtain $a_2b_2 = 1 - \ln 2$, and then $X''_{\text{макс}} = 1 - \ln 2 + T_u - 0{,}5\Delta_x$ or

$$X''_{\text{макс}} = T_u - 0{,}5\Delta_x + 0{,}3069. \tag{5}$$

From equations (4) and (5) it is seen that the maximal over-swing of the system in the transient mode is determined by the quantity T_u. The mutual position of of points $X'_{\text{МАКС}}$ and $X''_{\text{МАКС}}$ varies from the magnitude T_u.

Having equated equations (4) and (5), after transformations, we obtain the value T_u, for which $X'_{\text{МАКС}} = X''_{\text{МАКС}}$:

$$T_u = \ln(1 - 2e^{\Delta_x}). \tag{6}$$

The presence of regions of switching of function $\Phi(\delta)$ lying in the quadrants I and III of plane XY, is the reason for the emergence in the TsSS of the undamped oscillating motion in the steady--state mode. Each trajectory from any initial point with the lapse of a definite time interval enters into a defined region and from this moment no longer emerges from it.

Two kinds of closed trajectories of the representing point are possible in the steady-state mode. Figure 1 gives closed trajectories of types I and II. The trajectory of type I consists of two segments of the integral curve which correspond to the controlling action

3

$\Phi(\delta)$ 1 and $\Phi(\delta) = -1$. Points p and p' are switching points.

Trajectory II consists of segments of the integral curve with values $\Phi(\delta) = 1; \Phi(\delta) = 0$ and $\Phi(\delta) = -1$. Segments mn and m'n' correspond to the absence of the controlling action, i.e., $\Phi(\delta) = 0$. The time of the movement of the representing point from m to n (or from m' to n') is equal to $\Delta t = T_u$.

From Fig. 1 it is evident that the region of switching CHE (closed trajectory of type I) is considerably larger than the switching region MBHE (closed trajectory of type II). To determine parameters of the oscillating motion in the steady-state mode, let us examine the maximal possible closed trajectory, i.e., the trajectory of type I.* The period of the closed trajectory T_0 should consist of a finite even number of time segments T_u (sampling is considered). The time of the half-cycle $T_0/2$, i.e., the time between the switching points p and p' should correspond to

$$\frac{T_0}{2} = m T_u.$$

(7)

where m = 1, 2 and 3.

The maximal value of the velocity with a steady-state oscillating motion (at the moment of switching of the controlling action) can be found by assuming that in equation (2) $Y_0 = Y_a$; $Y = -Y_a$; $\Phi(\delta) = -1$; and $\tau = mT_u$. By examining the movement from point p to p', we find

$$Y_a = \frac{1 - e^{-mT_u}}{1 + e^{-mT_u}}.$$

(8)

According to equation (8), several limiting closed trajectories can be established in the system. It is necessary to determine the parameters of the maximally possible closed trajectory.

The period of the maximally possible closed trajectory $T_{0\text{max}} = 2mT_u$ must be less than the period of the closed trajectory, the switching points of which lie on lines AF and A'F'.**

From the condition of point transformation of line AF into line

---

*The presence of several closed trajectories of the representing point is possible in the region [1].

**Lines AF and A'F' are limits of regions of switching with the two-position characteristic of u the controlling element.

AF', it is possible to find the dependence of Y* on $T_ц$, where Y*
is the maximum velocity of the closed trajectory, the switching
points of which lie on the indicated line AF and A'F'.

The period of the steady-state oscillations in the system of
maximal amplitude can be determined from condition $Y_{a\ макс} < Y_a^*$.
The dependence of Y* on $T_ц$ is given on Fig. 2.

Fig. 2. Limit of the region of the
existence of the limiting closed
trajectory with the largest param-
eters.

Having used equation (1), let us define the doubled amplitude
of oscillations of the outlet coordinate $2A_x$ in the steady-state
mode

$$2A_x = \ln \frac{1}{(1 - Y_{a\ макс})(1 + Y_{a\ макс})}.$$ (9)

Dependences $Y_{a\ макс}$, T_0 and $2A_x$ define the basic relations of the
oscillating motion from parameters of the system.

Submitted
25 May 1970

Bibliography

1. *Изава К.* Релейные системы регулирования с импульсным действием. Труды
1-го ИФАК'а, т. 2, 1961.
2. *Страхов В. П., Кузнецова Е. Г.* Отображение динамики цифровой следящей си-
стемы с релейной характеристикой управляющего элемента на фазовой поверхности.
Изв. вузов СССР — «Приборостроение», 1971, т. XIV, № 3.